編號: 172

國立成功大學 109 學年度碩士班招生考試試題

系 所:電機工程學系


考試科目:控制系統

考試日期:0210, 節次:2


第1頁,共1頁

※ 考生請注意:本試題不可使用計算機。 請於答案卷(卡)作答,於本試題紙上作答者,不予計分。


- 1. Consider the two structures shown in Fig. 1.
 - (a) Please select H_1 and H_2 so that the nominal system outputs satisfy $F_1 = F_2 = F$, and assume $KH_1 > 0$. (10%)
 - (b) From the sensitivity definition, please determine the sensitivity of F with respect to K for these two structures, respectively. Which structure is less sensitive?. (15%)



2. Consider a closed-loop system described in Fig. 2, where C(s) = K and $G(s) = \frac{(s^2 + 1)}{(s - 1)^3}$. Please apply Nyquist plot design method to find the range of K such that the closed-loop system is stable. (25%)



3. For the motor, load, and torque-speed curve shown in Fig. 3, find the state-space representation in phase-variable form for the transfer function $G(s) = \theta_L(s)/E_a(s)$. (25%)



4. Design the values of K_1 and K_2 in the system of Fig. 4 to meet the following specifications: Steady-state error component due to a unit step disturbance is -0.015; steady-state error component due to a unit ramp input is 0.2. (25%)

